

AKG C411 L Specs

Transducer	Pre-Polarized Condenser Transducer
Polar Pattern	Figure 8
Frequency Response	10Hz to 18kHz
Dynamic Range (Typical)	<i>not specified by manufacturer</i>
Signal-to-Noise Ratio	<i>not specified by manufacturer</i>
Maximum Input Sound Level	96 / 103 dB SPL
Power Requirements	B 29 L Battery Power Supply MPA III L Power Supply Adapter AKG WMS Bodypack Transmitters
Output Impedance	200 ohms, unbalanced
Output Connectors	3-pin mini XLR
Pad	No
Low Frequency Roll-Off	No
Dimensions	1 x 0.6 x 0.4" (27 x 14 x 9.5mm)
Weight	18g (0.6 oz) / 150g (5.3 oz)

Packaging Info

Package Weight	0.43 lb
Box Dimensions (LxWxH)	6.45 x 4.9 x 2.5"