### PRODUCT HIGHLIGHTS

ClearOne's Wireless Microphone System is the most economical, versatile, and easily scalable wireless system in the market today with unprecedented ease-of-use and simple installation.

This microphone system complements other professional audio products from ClearOne including CONVERGE® Pro 1 & 2 Mixers, INTERACT Mixers, CONVERGE Matrix products. WS800 Receiver comes with and without DanteTM built-in audio networking.

Minimum Operating Frequency: 537 MHz Maximum Operating Frequency: 563 MHz Signal to Noise Ratio (SNR): 109 dB(A)

Operating Range: 300 ft 6.35mm (?1/4"): Yes

Height: 1.8" Width: 19" Depth: 6.5"

Weight (Approximate): 4.70 lb

#### **SPECIFICATIONS**

#### **General Information**

Manufacturer ClearOne

Manufacturer Part Number 910-6000-808-C-D
Manufacturer Website Address http://www.clearone.com

Brand Name ClearOne Product Model WS880

Product Name WS880 8-Channel Wireless Microphone System Receiver

Product Type Wireless Microphone System Receiver

**Technical Information** 

Minimum Operating Frequency537 MHzMaximum Operating Frequency563 MHzSignal to Noise Ratio (SNR)109 dB(A)Operating Range300 ft

Interfaces/Ports

6.35mm (?1?4") Yes

**Power Description** 

Input Voltage Range 100 V AC to 240 V AC

Miscellaneous

Additional Information Dante Network Capability

# Overview

## ClearOne WS880 8-Channel Wireless Microphone System Receiver

537 MHz to 563 MHz Operating Frequency - 300 ft Operating Range

ClearOne's Wireless Microphone System is the most economical, versatile, and easily scalable wireless system in the market today with unprecedented ease-of-use and simple installation.

This microphone system complements other professional audio products from ClearOne including CONVERGE® Pro 1 & 2 Mixers, INTERACT Mixers, CONVERGE Matrix products. WS800 Receiver comes with and without DanteTM built-in audio networking.