

# Yamaha STAGEPAS 400BT Specs

## Portable PA System

---

Speaker Configuration	<b>2 x</b> 2-Way Loudspeaker
-----------------------	------------------------------

---

Number of Input Channels	8
--------------------------	---

---

Amplifier Power Rating	400 W Peak (at 4 Ohms) 360 W RMS (at 4 Ohms)
------------------------	---

---

## Speakers

---

Enclosure Type	Bass-Reflex
----------------	-------------

---

HF Driver	1" / 25.4 mm Compression Driver
-----------	---------------------------------

---

HF Voice Coil	1" / 2.54 cm
---------------	--------------

---

LF Driver	8" / 20 cm Woofer
-----------	-------------------

---

## Signal Processing

---

EQ LF Shelf at 100 Hz

---

Effects Reverb

---

## Performance

---

Frequency Range 55 Hz to 20 kHz -10 dB

---

Maximum SPL 125 dB SPL

---

Coverage Angle 90° H x 60° V

---

## Connectivity

---

Audio I/O

- 2 x** XLR 3-Pin Mic/Line Input
- 1 x** Combo XLR-1/4" TRS Mic/Line Input
- 1 x** Combo XLR-1/4" TRS Mic/Line/Hi-Z Input
- 4 x** 1/4" TRS Line Input
- 1 x** Stereo RCA Coaxial Line Input
- 1 x** 1/8" / 3.5 mm TRS Line Input
- 2 x** 1/4" TS Speaker Output

**2 x** 1/4" TRS Monitor Output  
**1 x** 1/4" TRS Subwoofer Output  
**1 x** 1/4" TRS Footswitch Input

---

Phantom Power +30 V

---

Wireless Connectivity Bluetooth

---

## Bluetooth

---

Bluetooth 4.1

---

Bluetooth Profiles A2DP 1.2

---

Bluetooth Range 32.8' / 10 m

---

## Power

---

AC Input Power 100 to 240 VAC, 50 / 60 Hz

---

Power Consumption 30 W (Idle)  
70 W (1/8 Power)

---

AC Power Connector

IEC

---

## Physical

---

Transport Options

Handle (Top)

---

Mounting

1.4" / 35 mm Pole Socket ⓘ

---

Dimensions

**Speaker:**  
11.4 x 18.6 x 10.8" / 28.9 x 47.2 x 27.5 cm  
**Mixer:**  
12.1 x 7.1 x 4.6" / 30.8 x 18 x 11.6 cm

---

Weight

40.3 lb / 18.3 kg

---

## Packaging Info

---

Package Weight

49.75 lb

---

Box Dimensions (LxWxH)

26.5 x 22 x 14.9"

---